

ChangeMan ZMF

ERO Messages

8.3

Table of Contents

About this Guide	3
Audience and Scope	3
Guide to ChangeMan ZMF Documentation	3
Online Help	5
Typographical Conventions	6
ERO Messages	7
ERO Messages	7
Message Format	7
Message Descriptions	8
Legal Notice	62
Third-Party Notices	62
Specific notices	62

1. About this Guide

The purpose of this manual is to describe system messages and codes produced by ChangeMan® ZMF Enterprise Release Option (ERO).

Audience and Scope

This document is intended for ChangeMan ZMF ERO users, administrators, and the technical staff who install and support ChangeMan ZMF ERO software.

Guide to ChangeMan ZMF Documentation

The following sections provide basic information about ChangeMan ZMF documentation.

ChangeMan ZMF Documentation Suite

The ChangeMan ZMF documentation set includes the following manuals.

Manual	Description
Customization Guide	Provides information about ChangeMan ZMF skeletons, exits, and utility programs that will help you to customize the base product to fit your needs.
Db2 Option Getting Started Guide	Describes how to install and use the Db2 Option of ChangeMan ZMF to manage changes to Db2 components.
ERO Concepts	Discusses the concepts of the ERO Option of ChangeMan ZMF for managing releases containing change packages.
ERO Getting Started Guide	Explains how to install and use the ERO Option of ChangeMan ZMF to manage releases containing change packages.
IMS Option Getting Started Guide	Provides instructions for implementing and using the IMS Option of ChangeMan ZMF to manage changes to IMS components.
INFO Option Getting Started Guide	Describes two methods by which ChangeMan ZMF can communicate with other applications: <ul style="list-style-type: none">- Through a VSAM interface file.- Through the Tivoli Information Management for z/OS product from IBM.
Installation Guide	Provides step-by-step instructions for initial installation of ChangeMan ZMF. Assumes that no prior version is installed or that the installation will overlay the existing version.

Manual	Description
Java / zFS Getting Started Guide	Provides information about using ZMF to manage application components stored in USS file systems, especially Java application components.
Load Balancing Option Getting Started Guide	Explains how to install and use the Load Balancing Option of ChangeMan ZMF to connect to a ZMF instance from another CPU or MVS image.
M+R Getting Started Guide	Explains how to install and use the M+R Option of ChangeMan ZMF to consolidate multiple versions of source code and other text components.
M+R Quick Reference	Provides a summary of M+R Option commands in a handy pamphlet format.
Messages	Explains messages issued by ChangeMan ZMF, SERNET, and System Software Manager (SSM) used for the Staging Versions feature of ZMF.
Migration Guide	Provides guidance for upgrading ChangeMan ZMF
OFM Getting Started Guide	Explains how to install and use the Online Forms Manager (OFM) option of ChangeMan ZMF.
SER10TY User's Guide	Gives instructions for applying licenses to enable ChangeMan ZMF and its selectable options.
User's Guide	Describes how to use ChangeMan ZMF features and functions to manage changes to application components.

Using the Manuals

This section highlights some of the main Reader features. For more detailed information, see the Adobe Reader online help system. The PDF manuals include the following features:

- **Bookmarks.** All of the manuals contain predefined bookmarks that make it easy for you to quickly jump to a specific topic. By default, the bookmarks appear to the left of each online manual.
- **Links.** Cross-reference links within a manual enable you to jump to other sections within the manual with a single mouse click. These links appear in blue.
- **Comments.** All PDF documentation files that Serena delivers with ChangeMan ZMF have enabled commenting with Adobe Reader. Adobe Reader version 7 and higher has commenting features that enable you to post comments to and modify the contents of PDF documents. You access these features through the Comments item on the menu bar of the Adobe Reader.
- **Printing.** While viewing a manual, you can print the current page, a range of pages, or the entire manual.
- **Advanced search.** Starting with version 6, Adobe Reader includes an advanced search feature that enables you to search across multiple PDF files in a specified directory.

Searching the ChangeMan ZMF Documentation Suite

There is no cross-book index for the ChangeMan ZMF documentation suite. You can use the Advanced Search facility in Adobe Acrobat Reader to search the entire ZMF book set for information that you want. The following steps require Adobe Reader 6 or higher.

1. Download the ZMF All Documents Bundle ZIP file and the ZMF Readme to your workstation from the My Downloads tab on the Serena Support website.
2. Unzip the PDF files in the ZMF All Documents Bundle into an empty folder. Add the ZMF Readme to the folder.
3. In Adobe Reader, select Edit | Advanced Search (or press Shift+Ctrl+F).
4. Select the All PDF Documents in option and use Browse for Location in the drop-down menu to select the folder containing the ZMF documentation suite.
5. In the text box, enter the word or phrase that you want to find.
6. Optionally, select one or more of the additional search options, such as Whole words only and Case-Sensitive.
7. Click Search.
8. In the Results, expand a listed document to see all occurrences of the search argument in that PDF.
9. Click on any listed occurrence to open the PDF document to the found word or phrase.

Online Help

Online help is the primary source of information about ChangeMan ZMF. Online help is available as a tutorial, through Help screens, and in ISPF error messages.

Online Tutorial

ChangeMan ZMF includes an online tutorial that provides information about features and operations, from high-level descriptions of concepts to detailed descriptions of screen fields.

To view the tutorial table of contents, select option T from the Primary Option Menu, or jump to it from anywhere in ChangeMan ZMF by typing =T and pressing ENTER.

Press PF1 from anywhere in the Tutorial for a complete list of Tutorial navigation commands and PF keys.

Online Help Screens

If you have questions about how a ChangeMan ZMF screen works, you can view a help panel by pressing PF1 from anywhere on the screen.

Online Error Messages

If you make an invalid entry on a ChangeMan ZMF screen, or if you make an invalid request for a function, a short error message is displayed in the upper right corner of the screen. Press PF1 to display a longer error message that provides details about the error condition.

Remember that the long message does not display automatically. Request the long message by pressing PF1.

Typographical Conventions

The following typographical conventions are used in the online manuals and online help.

These typographical conventions are used to assist you when using the documentation; they are not meant to contradict or change any standard use of typographical conventions in the various product components or the host operating system.

Convention	Explanation
<i>italics</i>	Introduces new terms that you may not be familiar with and occasionally indicates emphasis.
**bold	Emphasizes important information and field names.
UPPERCASE	Indicates keys or key combinations that you can use. For example, press the ENTER key.
monospace	Indicates syntax examples, values that you specify, or results that you receive.
<i>monospaced italics</i>	Indicates names that are placeholders for values you specify; for example, filename.
vertical rule	Separates menus and their associated commands. For example, select File Copy means to select Copy from the File menu. Also, indicates mutually exclusive choices in a command syntax line.

2. ERO Messages

ERO Messages

This guide describes system messages and codes produced by ChangeMan® ZMF Enterprise Release Option (ERO).

It is intended for ChangeMan ZMF ERO users, administrators, and the technical staff who install and support ChangeMan ZMF ERO software.

It contains the following sections:

- [Message Format](#)
- [Message Descriptions](#)

Message Format

Each ISPF message can have two forms: a short message and a long message explanation.

The short message automatically displays in the upper right corner of the panel, overlaying any panel text in that area. See [1] in the sample panel below. The long message, which is more descriptive, displays when you press the PF1 HELP key after the short message displays. See [2] in the third line of the sample panel below.

```
CMRpanel ----- title of panel ----- short [1] message  
  
COMMAND ==>  
CMRnnnnx - [2]..long message  
panel text
```

The first three characters identify the application CMR, which stands for ChangeMan ZMF ERO. The next four digits *nnnn* refer to the message number. Use the message number to find an explanation for the message in this manual, or to request support from Serena Customer Support.

The last character, *x*, refers to the type of message:

- A refers to error messages that require Action.
- I refers to Informational messages that acknowledge the completion of a task.

Message Descriptions

The message descriptions list both the short and the long versions of the message, separated by the OR character , "|", for example:

Process Error | Release *{release}* - backout is already in progress.

The position of a variable value such as the release number are indicated by variable names enclosed in braces and italicized, for example:

{release}

Release Management General Messages

CMR0001I Invalid Status | Invalid Release status *{release}* must be in *{status}* status.

CMR0002I Release Undefined Package *{package}* not defined to a Release or Area.

CMR0003A Invalid Status | Invalid Release status *{status}* - must be in APR, REJ, DIS or BAK status.

CMR0004I No Prior Release | No Prior Releases found for release *{release}* Application *{application}*.

CMR0005I No Releases Found | No Other Releases found for Application *{application}*.

CMR0006A Release Already Defined | Release *{release}* has already been defined.

CMR0007A Global Params Updated | Release Global Parameters have been successfully updated.

CMR0008A Option not Available | Release Management is not licensed, contact administrator.

CMR0009A Invalid Status | Invalid Release status *{status}* - must be in BAS or INS status.

CMR0010A Process Error | Release *{release}* - install is already in progress.

CMR0011A Process Error | Release *{release}* - backout is already in progress.

CMR0012I Invalid Name | Invalid Release name specified, must begin with an alpha (A-Z).

CMR0013I Release Already Defined | Release *{release}* has already been defined copy not allowed.

CMR0014I Not a Prior Release | Release *{release}* has an install date greater than *{date}*.

Release Management Administration Messages

CMR0500A Undefined Release | Release {*release*} is undefined - contact Release Admin

CMR0501A Undefined Application | Undefined application {*application*} - contact local ADMIN

CMR0502A Application Locked | Application {*application*} globally locked for update

CMR0503A Undefined Prior Release | Undefined Prior Release {*release*} - contact Release ADMIN

CMR0504A Invalid Install Date | Release Install Date must be current or future

CMR0505A Invalid Install Date | Release Install to Date must be greater than from Date

CMR0506A Invalid Install Time | Release Install to Time must be greater than from Time

CMR0507A Invalid Install Time | Release Install Time must be 000000 to 235959 in hhmmss

CMR0510A Authorization Failed | You must have Global, Local, or RlseMgr authority to enter Admin

CMR0511A Authorization Failed | You must have Global or Release Manager Authority

CMR0512A Authorization Failed | You must have Global or Release Manager Authority

CMR0513A Authorization Failed | You must have Global Admin Authority to define the global HLQ

CMR0515A Authorization Failed | Your TSOID is not authorized to create the approval entity

CMR0516A Invalid Entity Name | Approval entity name is not defined in the security system

CMR0517A Invalid Area Rule | Area Rule, {*arearule*} can not be less than Release Rule {*releaserule*}

CMR0518I Applications Found | Release {*release*} still has applications attached

CMR0519A No Prior Release | There are no Prior Releases found for Release {*release*}

CMR0520A No Applications | There are no Applications attached to Release {release}

CMR0521A Release Created | Release {release} has been successfully created

CMR0522A Release Updated | Release {release} has been successfully updated

CMR0523A Release Deleted | Release {release} has been successfully deleted

CMR0524A Release Undeleted | Release {release} has been successfully undeleted

CMR0525A Release Updated | Prior Release {priorrelease} has been successfully updated for Release {updatedrelease}

CMR0526A Prior Release Deleted | Prior Release {priorrelease} has been successfully deleted for Release {release}

CMR0527A Application Joined | Application {application} has been successfully joined release

CMR0528A Application Updated | Application {application} has been successfully updated

CMR0529A Application Deleted | Application {*application*} has been successfully deleted

CMR0530A Libraries Deleted | Release {*release*} Area libraries successfully deleted

CMR0531I Invalid Name | Invalid Area name specified, must begin with an alpha (A-Z)

CMR0532A Undefined Approver | Invalid Area name specified, must begin with an alpha (A-Z)

CMR0533A Invalid Approver | Global Approver {*approver*} is not a release install Approver

CMR0534A Invalid Approver | Global Approver {*approver*} is not an area type approver

CMR0535A Invalid Approver | Global Approver {*approver*} is an associated approver

CMR0536A Invalid Approver | Global Approver {*approver*} is not an associated approver

CMR0537A Undefined Remote Site | Undefined Remote Site *{site}* - contact global ADMIN

CMR0538A Invalid Release Rule | Release Rule, *{releaserule}* can not be less than Global Rule *{globalrule}*

CMR0539A Invalid Install Time | Release Install to Time must be 1 min. more then from Time

CMR0540A Scheduler Not Allowed | Release Scheduler *{scheduler}* does not allow *{??????}* -contact Release ADMIN

CMR0541A Invalid Application | Application *{invalidapp}* cannot have application *{relatedapp}* as a related application

CMR0542A Invalid Input | Release and base ZMF applications are mutually exclusive

Release Management Audit Messages

CMR1000I Invalid Audit Level | Audit level *{level}* invalid - should be 0 to 5

CMR1001I Audit Failure | Area *{area}* failed the audit with a return code of *{code}*

CMR1002I Audit Failure | Package {package} failed the audit with a return code of {code}

CMR1003I Audit Failure | Area must be audited when audit rule is greater than 0

CMR1004A Audit Failure | If using autoresolve area must first pass TestArea function

Explanation: This is a SYSPRINT message from release audit program CMNRA000, which executes a test area when audit is submitted with the auto resolve option. The test area ensures that area components match the package libraries where they originated so that there is no possibility that auto resolve will overlay package components that have been changed or create orphans where package components have been deleted. This message indicates that the test area failed and that audit with auto resolve is halted with RC=12.

Solution: Resolve the issues detected by test area, and then resubmit release audit with auto resolve `

CMR1005I (No short message) | Autoresolve requested

Explanation: This is a SYSPRINT message from the release audit program CMNRA000 to indicate that release audit was submitted with the auto resolve option.

Solution: None

CMR1006I (No short message) | Audited area has passed TestArea function, autoresolve will proceed

Explanation: This is a SYSPRINT message from the release audit program CMNRA000, which executes a test area when release audit is submitted with the auto resolve option. The test area ensures that area components match the package libraries where they originated so that there is no possibility that auto resolve will overlay package components that have been changed or create orphans where package components have been deleted. This message indicates that test area was passed and that audit with auto resolve will continue.

Solution: None `

CMR1007I (No short message) | Ignore Higher Areas has been requested

Explanation: This is a SYSPRINT message from the release audit program CMNRA000 to indicate that release audit has been requested with the ignore higher areas (IHA) option.

Solution: None

CMR1008I (No short message) | Conditional processing of higher areas has been requested, checking for start areas

Explanation: This is a SYSPRINT message from the release audit program CMNRA000 to indicate that audit was requested with the conditional processing of the ignore higher areas (IHA) option.

Solution: None`

CMR1009I (No short message) | One start area found, ignoring higher areas for this audit

Explanation: This is a SYSPRINT message from release audit program CMNRA000 to indicate that, while checking areas for conditional IHA processing, audit found only a single start area in the release. Audit will proceed to ignore higher areas for this execution.

Solution: None

CMR1010I (No short message) | Multiple start areas found, higher areas will not be ignored

Explanation: This is a SYSPRINT message from the release audit program CMNRA000 to indicate, while checking areas for conditional IHA processing, audit found multiple start areas in the release. Audit will not ignore higher areas for this execution.

Solution: None

CMR1011I (No short message) | IHA=YES processing in effect, area audit rc will not be updated

Explanation: This is a SYSPRINT message from the release audit program CMNRA000 to indicate that audit is executing with IHA=YES processing in effect, so the area audit rc will not be updated.

Solution: None

CMR1012I (No short message) | Area integrity check is underway

Explanation: This is a SYSPRINT message from the release audit program CMNRA000 to indicate that an area integrity check has been requested (INT=YES) before normal audit processing begins. This check is currently taking place.

Solution: None.

CMR1013A (No short message) | Area failed integrity check, details follow

Explanation: This is a SYSPRINT message from the release audit program CMNRA000 to indicate that the requested area integrity check has failed. Details to follow.

Solution: Investigate the details that follow, similar to this example:

Member missing STEV/COPY: COPY01

Member missing STEV/LOD: PGM1

Member missing STEV/LST: PGM1 Member missing STEV/SUB: SUB1

Member missing STEV/LOD: RENAME01.

CMR1014I (No short message) | Audited area has passed the integrity check

Explanation: This is a SYSPRINT message from the release audit program CMNRA000 to indicate that the requested area integrity check has passed.

Solution: None

CMR1066I Undefined Security Entity | Security entity {entity} undefined; contact security ADMIN

CMR1090A Authorization Failed | Application access denied - contact local ADMIN

CMR1094A Unauthorized Access | {entity} entity authorization required

**CMR1104I (No short message) | BUN Number not available for xxxxxxxx in
yyyyyyyy – ignored**

Explanation: This is a SYSPRINT message from the release audit program CMNRA000 that indicates audit was unable to find a BUN for a copybook (xxxxxxx) being used by source (yyyyyy) in baseline I/A. No audit analysis will be performed for this relationship.

Solution: This is usually caused by the baseline I/A row not having an application and/or libtype for the copybook as a result of an error during the build of the source component in the package which last baselined it. If you cannot determine the cause of this error, contact Micro Focus customer support for assistance.

CMR1120A (No short message) | CIM Record not found for: *nnnnnn

Explanation: This is a SYSPRINT message from the release audit program CMNRA000 to indicate that audit has been unable to find a CIM record for *nnnnn*.

Solution: This may be the result of an incomplete action (such as an interrupted checkin). Try re-establishing the affected component in the release. If the problem persists contact Micro Focus customer support. |

CMR1121A | (No short message) | HST Record not found for: *nnnnnn

Explanation: This is a SYSPRINT message from the release audit program CMNRA000 to indicate that audit has been unable to find a HST record for *nnnnn*.

Solution: This may be the result of an incomplete action (such as an interrupted checkin). Try re-establishing the affected component in the release. If the problem persists contact Micro Focus customer support.

**CMR1122A (No short message) | Consolidated baseline build - Open failed for:
*nnnnnn**

Explanation: This is a SYSPRINT message from the release audit program CMNRA000 to indicate that audit has been unable to open library *nnnnn* during consolidated baseline build.

Solution: This message should be accompanied by system generated error messages from the attempt to open the library. There is either something wrong with the library itself or ZMF administration is incorrect (e.g. pointing to a non-existent library).

CMR1123I (No short message) | Audit return code update failed for the following reason: reason |

Explanation: This is a SYSPRINT message from the release audit program CMNRA000 to indicate that the area audit return code update has failed for the reason **reason**.

Solution: Examine and rectify the **reason** `

CMR1124I (No short message) | The CMNERRORTYPES DB2 table is empty, processing continues with the default error return codes |

Explanation: This is a SYSPRINT message from the release audit program CMNRA000 to indicate that the CMNERRORTYPES Db2 table is empty so processing continues with default (hard coded) error codes.

Solution: Populate the CMNERRORTYPES table as shown in the CMNLDERT sample JCL member `

CMR1125I (No short message) | Analysis complete, release audit return code is: rc

Explanation: This is a SYSPRINT message from the release audit program CMNRA000 to indicate that audit analysis has completed and has a return code of **rc**.

Solution: None

CMR1126I (No short message) | Error code ???? has been marked as ineligible for autoresolve

Explanation: This is a SYSPRINT message from the release audit program CMNRA000 to indicate that this particular error code will not result in an autoresolve job being submitted.

Solution: This is informational only, these error codes cannot be addressed by autoresolve `

CMR1127I (No short message) | BUN Number not available for xxxxxxxx in yyyyyyyy – ignored

Explanation: This is a SYSPRINT message from the release audit program CMNRA000 that indicates audit was unable to find a BUN for a subroutine (xxxxxxx) being used by composite load module (yyyyyyy) in baseline I/A. No audit analysis will be performed for this relationship.

Solution: This is usually caused by the baseline I/A row not having an application and/or libtype for the subroutine as a result of an error during the build of the composite load module in the package which last baselined it. If you cannot determine the cause of this error, contact Micro Focus customer support for assistance .

CMR1128I (No short message) | BUN Number not available for xxxxxxxx referenced by yyyyyyyy – ignored

Explanation: This is a SYSPRINT message from the release audit program CMNRA000 that indicates audit was unable to find a BUN for load module (xxxxxxx) being referenced by link control component (yyyyyyy) in baseline I/A. No audit analysis will be performed for this relationship.

Solution: This is usually caused by the baseline I/A row not having an application and/or libtype for the load module as a result of an error during the build, which uses the link control card (LCT) in the package that last baselined it. If you cannot determine the cause of this error, contact Micro Focus customer support for assistance.

Release Management Block Messages

CMR1500A Invalid Blocking Rule | Blocking rule {rule} invalid - should be 0

CMR1501I Release Blocked | Release {release} has been successfully blocked

CMR1502I Area Blocked | Release {release} Area {area} has been successfully blocked

CMR1503I Audit Failure | Area must be audited when blocking rule is greater than 0

CMR1504A Authorization Failed | Release Manager Authority required to Block or Unblock

CMR1505A Authorization Failed | Release Manager Authority required to Revert

CMR1506I Components Failed | Release {release/area} and package components do not match

Explanation: Test area failed, detecting differences between components in the indicated release area and the package libraries where the components originated.

Solution: Resolve the issues detected by test area. Resubmit test area or the function that you executed that initiated a test area, such as release audit with the auto resolve option.

CMR1507I Components Passed | Release {release} and package components match

CMR1527I Node Outstanding | Package {package} installation JCL build outstanding

Release Management Backout Messages

CMR2000I Release Reverted | Release {release} has been successfully reverted

CMR2001I Backouts Submitted | Release {release} package backouts have been submitted

CMR2002I Backout Not Allowed | Package {*package*} is attached to release {*release*}, backout release

Release Management Checkin Messages

CMR2500A Invalid Option | Release package is in {*status*} status - must be DEV, FRZ, or APR

CMR2501A Package Not Found | Release package {*package*} does not exist in the package master

CMR2502A Package Memo Deleted | Release package {*package*} is in memo deleted status

CMR2503A Install Date Error | Package install date must be current or future for checkin

CMR2504A Authorization Failed | Release application access denied - contact Release Admin

CMR2505A Invalid Package Level | Release package level must be simple

CMR2506A Invalid Package Id | Release package ID must be a planned permanent package

CMR2507A Undefined Application | Undefined release application {*application*} - contact Release Admin

CMR2508A No Components Found | No release package components found in the package master

**CMR2509A Storage Error | Memory unavailable for build of dynamic panel.
Getmain RC = {*returncode*}**

**CMR2510A Storage Error | Memory unavailable for build of component list.
Getmain RC = {*returncode*}**

CMR2511A Invalid Date | {*date*} is an invalid Gregorian date for checkin function

CMR2512A Invalid Date Range | FROM date {*date*} is more current than the TO date for checkin

CMR2513I Select Error | Component override not allowed on a locked component

CMR2514A Release Undefined | Package {*package*} not defined to a Release - contact Release Admin

CMR2515A Release Invalid | {??????} not defined to Release {release} - contact Release Admin

CMR2516A Area Invalid | {??????} not defined to Area {area} - contact Release Admin

CMR2517A Area Undefined | Package {package} not defined to an Area - contact Release Admin

CMR2518A Invalid Check-in Rule | Check-in Rule {rule} invalid - should be 0 - 7

CMR2519A Run Table Error | No entries found on select request to Baseline Unique Table

CMR2520A Storage Error | Memory unavailable for build of Selection Idx. Getmain RC = {returncode}

CMR2521A DB2 Open Error | Error attempting open of DB2 Call Attach Facility

CMR2522A DB2 Close Error | Error attempting close of the DB2 Call Attach Facility

CMR2523A Storage Error | Memory unavailable for build of Duplicate list. Getmain RC = {returncode}

**CMR2524A Storage Error | Memory unavailable for build of Duplicate Indx. Getmain
RC = {returncode}**

**CMR2525A Storage Error | Memory unavailable for build of Duplic panel. Getmain
RC = {returncode}**

**CMR2526I Select Error | Component override not allowed on a different release
package**

CMR2527I Select Error | Not all components displayed can be selected for override

**CMR2528I Select Error | Component override not allowed on lib type without a valid
Bun**

**CMR2529I No Selections | No components selected for Checkin into target area
{area}**

**CMR2530I Not Qualified | No components selected for Checkin qualify for area
{area}**

**CMR2531A Rlse not Found | Release Name Id {id} does not exist in the package
master**

**CMR2532A Area not Found | Release Area Id {id} does not exist in the package
master**

CMR2533I Action in Progress | Checkin bypassed due to {??????} in progress for area {area}

CMR2534I Area Blocked | Checkin bypassed for {??????} due to area {area} is blocked

CMR2535A Invalid Rule | Invalid or conflicting checkin rules detected for area {area}

CMR2536A Rule Violation | Checkin rule for area {area} requires {??????} to be frozen

CMR2537A Storage Error | Memory unavailable for build of Lib Type Table. Getmain RC = {returncode}

CMR2538A Storage Error | Memory unavailable for build of Approval List. Getmain RC = {returncode}

CMR2539A No Approver Record | Release Id {id} approver record not found in package master

CMR2540A No Approver Record | Release Area {area} approver record not found in package master

CMR2541A Storage Error | Memory unavailable for build of User List. Getmain RC = {returncode}

**CMR2542A Storage Error | Memory unavailable for build of Bun Table Area.
Getmain RC = {returncode}**

**CMR2543A Storage Error | Memory unavailable for build of Src-Lod List. Getmain
RC = {returncode}**

**CMR2544A Storage Error | Memory unavailable for build of Src-Lod panel. Getmain
RC = {returncode}**

CMR2545I Select Error | Component override not allowed on a different user id

**CMR2546A Storage Error | Memory unavailable for build of UCA Work Area.
Getmain RC = {returncode}**

**CMR2547A Package Master Error | Global Record 0 not found during build of
Release Area data sets**

**CMR2548A HLQ Not Found | Release high level qualifier name not found in Global
Record 0**

**CMR2549A Storage Error | Memory unavailable for the area names table. Getmain
RC = {returncode}**

CMR2550A Library Error | Release Id {id} lib type record not found in package master

CMR2551A Storage Error | Memory unavailable for area dataset table. Getmain RC = {returncode}```

CMR2552A No Area Libraries | No release area library types defined in the package master

CMR2553A Storage Error | Memory unavailable for area data set panel. Getmain RC = {returncode}```

CMR2554A No Release Areas | No release area names defined for Release Id {id}

CMR2555A Storage Error | Memory unavailable for allocation progress. Getmain RC = {returncode}

CMR2556A I/O Error | In progress indicator not set to ON due to Pmast I/O error

CMR2557A I/O Error | In progress indicator not set to OFF due to Pmast I/O error

CMR2558A Storage Error | Memory unavailable for checkin result list. Getmain RC = {returncode}

CMR2559A Copy Error | Error on Copy to Target Area {area}

CMR2560A Storage Error | Memory unavailable for summary panel area. Getmain RC = {returncode}

CMR2561A DB2 Error | DB2 error attempting commit for delete of rows in CIM Table

CMR2562A DB2 Error | DB2 error attempting commit for insert of rows in CIM Table

CMR2563A Storage Error | Memory unavailable for member list lib Area. Getmain RC = {returncode}

CMR2564A List Error | Error on member list for {??????}

CMR2565A Storage Error | Memory unavailable for member list area. Getmain RC = {returncode}

CMR2566I Select Error | Component override not allowed-member not found in data set

CMR2567I Select Error | Component override not allowed-component authorization required

CMR2568A Storage Error | Memory unavailable for component load area. Getmain RC = {returncode}

CMR2569A DB2 Error | DB2 error attempting insert of history records in HST Table

CMR2570A DB2 Error | DB2 error attempting commit for insert of rows in HST Table

CMR2571A I/O Error | I/O error on log file attempting update for Checkin activity

CMR2572A Invalid Rule | Invalid or conflicting Audit rules detected for area *{area}*

CMR2573A Invalid Job Card | Change Man Exit 8 indicates invalid job card information

CMR2574A Ispfile Not Found | {??????} ISPF data set was not found

CMR2575A Ftopen Error | Error on file tailoring open for skel {??????}. RC = *{returncode}*

CMR2576A Ftincl Error | Error on file tailoring include for skel {??????}. RC = *{returncode}*

CMR2577A Ftclose Error | Error on file tailoring close for skel {??????}. RC = *{returncode}*

CMR2578A Audit Submit Error | Error on submit of audit job for target area *{area}*

CMR2579I Audit Job Submitted | Job submitted to audit area *{area}* of release *{release}*

CMR2580A I/O Error | I/O error on log file attempting update for Audit activity

CMR2581A Authorization Failed | Release checkin entity access denied - contact Release Admin

CMR2582A Authorization Failed | Release Id access denied - contact Release Administrator

CMR2583A Authorization Failed | Release checkin entity not defined - contact Release Admin

CMR2584A Notification Error | Release area *{area}* notification error for checkin approvers

CMR2585I Notify Action | Area *{area}* of release *{release}* waiting for checkin approval request by user *{userid}*

CMR2586A Authorization Failed | Release Id entity *{??????}* not defined - contact Rlse Admin

CMR2587A I/O Error | Notify indicator not set for *{??????}* due to Pmast I/O error

CMR2588A Storage Error | Memory unavailable for approver work area. Getmain RC = *{returncode}*

CMR2589A Notify Failed | Checkin approval required, no approvers defined. Contact Rlse Admin

CMR2590A Notify Failed | Checkin approval required, no users defined. Contact Rlse Admin

CMR2591A CAF Error | DB2 CAF error processing {??????} request

CMR2592A No Components Found | No release components were found for area {area}

CMR2592A Checkin Not Approved | Checkin approval required for area {area} . Contact Release Admin

CMR2593A Checkin Not Approved | Checkin approval required for area {area} . Contact Release Admin

CMR2594A Rule Violation | Checkin rule for area {area} requires {??????} to be blocked

CMR2595A Checkoff Not Approved | Checkoff approval required for area {area} . Contact Release Admin

CMR2595A Checkin Not Allowed | Checkin of final release area {area} not allowed

CMR2596I Checkin Not Allowed | Checkin of final release area {area} not allowed

CMR2597I Audit Failure | Area must be audited when check-in rule is 1, 4, 5 or 7

CMR2598A Rule Violation | Checkin rule for area {*area*} requires {??????} to be frozen

CMR2599I Audit Failure | Package must be audited when check-in rule is 1, 4, 5 or 7

CMR2600I Job Submitted | Job to batch check-in has been submitted

CMR2601A DB2 Error | Insert of i/a table records failed, see server SERPRINT for details

CMR2602A DB2 Error | Delete of i/a table records failed, see server SERPRINT for details

CMR2610I Checkin Complete | Checkin completed {??????} of {??????} components for area {*area*}

CMR2700I Select Error | Component override not allowed, override not specified

CMR2701I Select Error | Library Type BUN (Baseline Unique Number) for {??????} not found

CMR2702I Select Error | Component {??????} is locked by {??????}

CMR2730I Checkin Exit Error | Checkin halted by system exit, please contact administrator

CMR2731I No Component Found | System exit removed all selected components, contact administrator

CMR2800I Select Error | Source {??????} has related components checked in

Release Management Generate Messages

CMR3000A Invalid Generate Rule | Generate Rule {rule} invalid - should be 0 - 6

CMR3050I Invalid Option | No Area libraries to process

Release Management Install Messages

CMR3500I Undefined Install Site | Release Application {*application*} Install Site {*site*} not found

CMR3501A Invalid Option | Release Application {*application*} Install Site {*site*} not found

Release Management Retrieve Messages

CMR4000A Invalid Retrieve Rule | Retrieve Rule {rule} invalid - should be 0 - 3

CMR4001I Area Blocked | Retrieve bypassed for {??????} due to area {*area*} is blocked

CMR4002A Invalid Rule | Invalid or conflicting retrieve rules detected for area {area}

CMR4003I Action in Progress | Retrieve bypassed due to {??????} in progress for area {area}

CMR4004A Authorization Failed | Release retrieve entity access denied - contact Release Admin

CMR4005A Authorization Failed | Release retrieve entity not defined - contact Release Admin

CMR4006A Install Date Error | Package install date must be current or future date for retrieve

CMR4007A Invalid Date | {date} is an invalid Gregorian date for retrieve function

CMR4008A Invalid Date Range | FROM date {date} is more current than the TO date for retrieve

CMR4009I No Selections | No components selected for Retrieve from target area {area}

CMR4010A I/O Error | I/O error on log file attempting update for Retrieve activity

CMR4011A Storage Error | Memory unavailable for retrieve result list. Getmain RC = {returncode}

CMR4012A Delete Error | Error on Delete from Target Area {*area*}

CMR4013I Not Qualified | No components selected for Retrieve qualify for area {*area*}

CMR4014I No Component | Component {??????} not found for target area {*area*}

CMR4020I Job Submitted | Job to batch retrieve has been submitted

CMR4030I Retrieve Exit Error | Retrieve halted by system exit, please contact administrator

CMR4031I No Component Found | Retrieve halted by system exit, please contact administrator

CMR4040I Retrieve Complete | Retrieve completed {??????} of {??????} components for area {*area*}

CMR4210A INVALID DATE | {*date*} is an invalid Gregorian date

CMR4400I Release Detach Error | Package {*package*} still has components not retrieved from Release

CMR4401I Retrieve Error | Package {*package*} has no components to retrieve from Release

CMR4402I Release Detach Error | Package *{package}* has components in the Release, RP to Retrieve

Release Management Unblock Messages

CMR4500I Release Unblocked | Release *{release}* has been successfully unblocked

CMR4501I Area Unblocked | Release *{release}* Area *{area}* has been successfully unblocked

Release Management Housekeeping Messages

CMR5051A Versions not allowed | Save staging versions not allowed for RECFM "U" library types

CMR5052A Versions not allowed | Save staging versions not allowed for library type like other

Release Management Library Type Messages

CMR5500A | Undefined Library Type | Library Type *{type}* is undefined for release *{release}*

CMR5501A | Undefined Library Type | SYSLIB Library Type *{type}* is undefined

CMR5502A | Not All Changes Allowed | Library Type(s) {type} area libraries already allocated

CMR5503I | SYSLIB Not Found | SYSLIB definition for {??????} not found

CMR5504I | Invalid SYSLIB Type | SYSLIB Library Type {type} has an invalid like Value {??????}

CMR5505I | Invalid SYSLIB Type | SYSLIB Library Type {type} invalid for copylib request

CMR5506I | Target LibType Error | Library Type {type} has no target library type defined

CMR5507I | No More Library Types | There are no more library types for related application found to add

CMR5508A | No Library Types Added | There are no more library types for related application found to add

CMR5509A | No More Library Types | There are no more {??????} library types found

CMR5510A | No More Langs/Procs | No more languages/procedures found for library type {type}

CMR5511A | Library Type Updated | Library Type {*type*} has been successfully updated

CMR5512A | Library Type Deleted | Library Type {*type*} has been successfully deleted

CMR5513A | SYSLIB Updated | SYSLIB {??????} has been successfully updated

CMR5514A | SYSLIB Deleted | SYSLIB {??????} has been successfully deleted

CMR5515A | Undefined Lang/Proc | Language/Procedure {??????} undefined for application {*application*}

CMR5516A | Undefined LibType | Application does not have release LibType {*libtype*} defined

CMR5517A | Invalid Numeric | Invalid numeric data {??????} for {??????}

CMR5518A | Undefined Library Type | Global Library Type {*type*} is undefined

CMR5519A | Undefined Library Type | Application {*application*} Library Type {*type*} is undefined

CMR5520I | Invalid Library Type | Only source library types have copylib concatenations

CMR5521I | Libraries Allocated | Release {*release*} area libraries allocated for library type {*type*}

Release Management Approval Messages

CMR6000A | Invalid Approval Rule | Approval Rule {rule} invalid - should be 0 - 3

CMR6001A | Undefined Approver | Approver entity {??????} is not defined contact Release Admin

CMR6002A | Invalid Approver Code | Approver code {code} is not valid, A and R are valid

CMR6010A | Approver association | Approver association does not exist for {??????}

CMR6011I | Approval Error | Approval/Rejection previously executed for this approver

CMR6012I | Sequence Error | Your approval/rejection is not next on the hierarchy list

CMR6013I | Reject Not Found | Release {*release*} has never been rejected

CMR6014I | Reject Not Found | Release {*release*} Area {*area*} has never been rejected

CMR6015I | Already Notified | Release {*release*} Area {*area*} approvers already notified

CMR6016I Invalid Value	 Check-in value {value} invalid, must be Y or N
CMR6017I Invalid Value	 Check-off value {value} invalid, must be Y or N
CMR6018I Invalid Approver exclusive	 Check-in and Check-off approvers are mutually exclusive
CMR6019I Invalid Approver approver	 Approver must be either a Check-in or Check-off approver
CMR6020I Invalid Value	 Associated value {value} invalid, must be Y or N
CMR6021I Invalid Value	 Install approver value {value} invalid, must be Y or N
CMR6022I Invalid Approver Install approver	 Approver must be either a Check-in, Check-off or Install approver
CMR6023I Invalid Association association entered	 Approver association must have at least one association entered
CMR6024I Approver Error {area}	 No Approvers Notified for release {release} Area {area}

CMR6025A | Approvers Notified | Updates for {??????} approvers denied already notified

CMR6026A | Approver Already Defined | Approver {??????} has already been defined

CMR6027A | No Global Approvers | There are no more Global Approvers to list

CMR6028A | Global Approver Updated | Global Approver {??????} has been successfully updated

CMR6029A | Global Approver Created | Global Approver {??????} has been successfully created

CMR6030A | Global Approver Deleted | Global Approver {??????} has been successfully deleted

CMR6031A | Install Approver Updated | Install Approver {??????} has been successfully updated

CMR6032A | Install Approver Deleted | Install Approver {??????} has been successfully deleted

CMR6033A | Area Approver Updated | Area Approver {??????} has been successfully updated

CMR6034A | Area Approver Deleted | Area Approver {??????} has been successfully deleted

CMR6035I | Release Approved | Approver {??????} has successfully approved Release {*release*}

CMR6036I | Release Rejected | Approver {??????} has successfully rejected Release {*release*}

CMR6037I | Release Approved | Release {*release*} has been approved

CMR6038I | Release Rejected | Release {*release*} has been rejected

CMR6039I | Area Approvers Notified | Release {*release*} Area {*area*} check-off approvers notified

CMR6040I | Area Approvers Notified | Release {*release*} Area {*area*} check-in approvers notified

CMR6041I | Area Approvers Reset | Release {*release*} Area {*area*} check-in approvers have been reset

CMR6042I | Area Approved | Approver {??????} has successfully approved Area {*area*}

CMR60431 | Area Rejected | Approver {??????} has successfully rejected Area {area}

CMR60441 | Area Approved check-in | Release {release} Area {area} has been approved for check-in

CMR60451 | Area Rejected check-in | Release {release} Area {area} has been rejected for check-in

CMR60461 | Area Approved approved | Release {release} Area {area} has been check-off approved

CMR60471 | Area Rejected check-off | Release {release} Area {area} has been rejected for check-off

CMR60481 | Invalid Approver | Approver entity {??????} is not a Check-in approver

CMR60491 | Invalid Approver | Approver entity {??????} is not a Check-off approver

CMR60501 | Invalid Approver | Approver entity {??????} is not a Release approver

CMR60511 | Area Approved check-in approved | Release {release} Area {area} has already been check-in approved

CMR60521 | Area Approved check-off approved | Release {release} Area {area} has already been check-off approved

Release Management Checkout Messages

CMR6500A Invalid Option | Release package is in {??????} status; must be in DEV status

CMR6502I Action in Progress | Checkout bypassed due to {??????} in progress for area {area}

CMR6503A Install Date Error | Package install date must be current or future date for checkout

CMR6504I No Information | No information found for {??????} request

CMR6507A Invalid Date | {date} is an invalid Gregorian date for checkout function

CMR6508A Invalid Date Range | FROM date {date} is more current than the TO date for checkout

CMR6509I No Selections | No components selected for Checkout into target area {area}

CMR6510A I/O Error | I/O error on log file attempting update for Checkout activity

CMR6511A Storage Error | Memory unavailable for checkout result list. Getmain RC = {returncode}

CMR6512A Copy Error | Error on Copy from Target Area {area}

CMR6513A No Library Types | No application library types defined in the package master

CMR6514A Update Alloc Error | Unable to update deferred allocation for {??????} library type

CMR6515I Not Qualified | No components selected for Checkout qualify for area {area}

CMR6516I No Areas Found | No Areas were found for release {release} that allow checkout

Release Management Area Messages

CMR7000A Undefined Area | Area {area} is undefined for release {release}

CMR7001I Invalid Status | Release {release} Area {area} is not blocked

CMR7002I Invalid Status | Release {release} Area {area} is already blocked

CMR7003I Invalid Status | Release {release} Area {area} has not been approved for check-in

CMR7004A Incomplete Areas | No Subsystem Area found for Release {release}

CMR7005A Incomplete Areas | No System Area found for Release {release}

CMR7006A Incomplete Areas | No starting Subsystem Area found for Release {release}

CMR7007A Incomplete Areas | No ending System Area found for Release {release}

CMR7008A Invalid Ending Area | Areas can only have one ending System Area

CMR7009A Area Config. Invalid | Area {area} is not a valid starting SubSystem Area

CMR7010A Undefined Area | Area {area1} contains next/prior Area {area2} that is undefined

CMR7011A Area Config. Invalid | Area {area} is not a valid ending System Area

CMR7012A Area Config. Invalid | Area {area} can not have itself as a next/ prior area

CMR7013A Area Config. Invalid | Area {area1} Next Area {area2} is not a higher step number

CMR7014A Area Config. Invalid | Area {area1} Prior Area {area2} is not a lower step number

CMR7015A Area Config. Invalid | System Area {area1} can not have Subsystem Area {area2} as Next Area

CMR7016A Area Config. Invalid | Subsystem Area {area1} can not have System Area {area2} as Prior Area

CMR7017A Area Config. Invalid | Area {area} has both Next and Prior Areas the same

CMR7018A Area Config. Invalid | Area {area1} has Next Area beyond first System Area {area2}

CMR7019A Area Config. Invalid | System Area {area1} Next Area not next Area {area2} in chain

CMR7020A Area Config. Invalid | System Area {area1} Prior Area not Prior Area {area2} in chain

CMR7021A Area Config. Invalid | Starting Area {area} has broken froward chain to Final Area

CMR7022A Area Config. Invalid | Area {area} has no backward chain to a Starting Subsystem Area

CMR7023A Area Config. Invalid | Area {area1} has broken backward chain Prior Area {area2}

CMR7024A Area Already Defined Invalid | Area {area} has already been defined for release {release}

CMR7025A Area Created | Area {area} has been successfully created

CMR7026A Area Updated | Area {area} has been successfully updated

CMR7027A Area deleted | Area {area} has been successfully deleted

CMR7028A Areas Undefined | Release {release} has no Areas defined

CMR7029I Areas Unblocked | Area {area} is not blocked in Release {release}

CMR7030I Nothing In Progress | Area {area} has nothing in progress at this time

CMR7031I No Resets Processed | Area {area} had no in progress indicators selected for reset

CMR7032I In Progress Reset | Area {area} in progress {??????} indicator reset

CMR7033A Undefined Entity | Entity {??????} is not defined for {??????} rule contact Admin

CMR7034I Access Denied | Access denied for entity {??????} for {??????} rule

CMR7035I Invalid Status | Release {release} Area {area} has not been approved for check-off

CMR7036I Invalid Command | Area package component test is only valid for system areas

CMR7037I Invalid Status | Release {release} Area {area} has not been approved for check-in

CMR7038I Invalid Reason | Diff version in final area; Check-in from package

CMR7039A Invalid Status | Clean-up of DEV packages not allowed; check release settings

CMR7040A Invalid Status | Clean-up of FRZ packages not allowed; check release settings

CMR7041A Invalid Status | Clean-up of APR packages not allowed; check release settings

CMR7042I Invalid Status | Only DEV, FRZ, and APR packages can be auto cleanup

CMR7043I Invalid Status | Not all failed components can be selected for clean-up

CMR7200I Lock Not Found | Area component lock(s) not found for specified lock

CMR7201I Duplicate Lock | Duplicate area component lock found for {??????}

CMR7202I Locks Deleted | Area component locks deleted for {??????}

Release Packages Messages

CMR7500A No Packages | Release *{release}* has no packages attached

CMR7501I Packages Found | Release *{release}* still has packages attached

CMR7502I Pkg/Appl Match Error | Package *{package}* does not match application *{application}*

CMR7503I Release Package Error | Package *{package}* is not attached to Release *{release}*

CMR7504I Area Package Error | Package *{package}* is not attached to Area *{area}*

CMR7505I Packages Found | Release application *{application}* still has packages attached

CMR7506I Package Delete Error | Package {*package*} is still attached to release {*release*}

CMR7507I Package Detached | Package {*package*} is now detached from release {*release*}

CMR7508I Package Updated | Package {*package*} is now attached to release {*release*}

CMR7509I No Releases Found | No Releases found with Packages attached

CMR7509I No Releases Found | No Releases found with Packages attached

CMR7510I Invalid Status | Option only for Packages in DEV, FRZ or APR status

CMR7511I Audit Failure | Package {*package*} failed the audit with a return code of {*returncode*}

CMR7512I Invalid Install Date | Install date must be within release date {*date1*} to {*date2*}

CMR7513I Invalid Install Time | Install time must be within release time {*time1*} to {*time2*}

CMR7514I Package not checked in | Package {*package*} has not been checked into Release {*release*}

CMR7515I Package not Approved | Package {*package*} has not been approved for Release {*release*}

CMR7516I Invalid Install info Package {*package*} install outside release {*release*} install range

CMR7517I Component Checked In | Component {*??????*} is checked into release {*release*}

CMR7518I Invalid Status | Package {*package*} must be in {*??????*} status

CMR7520I Select Error | Multiple selections not allowed, select only one

CMR7530I Attach Error | Package attach halted by system exit, please contact administrator

CMR7531I Detach Error | Package detach halted by system exit, please contact administrator

Release Management General Services Messages

CMR8000I Process error | {??????} was not specified

CMR8001I No Information | No information found for {??????} request

CMR8002I Service completed | {??????} service completed

CMR8003I List continuing | The {??????} list is continuing

CMR8240A Process Error | {??????} is already linked to {??????}

CMR8240A Process Error | {??????} is already linked to {??????}

CMR8490I Process Error | {??????} was not specified

CMR8502I Process Error | {??????} is invalid

CMR8600I List complete | The {??????} list is complete

CMR8605I List continuing | The {??????} list is continuing

CMR8646A Duplicate Record | Package Master record already exists

CMR8700I Service completed | {??????} service completed

CMR8701I Request pending | {??????} service request pending

CMR8702I Request Cancelled | {??????} service request cancelled

CMR8703I Service failed | {??????} service failed

CMR8730I Invalid input | Input field {??????} has invalid data: {??????}

CMR8732I Service error | Data set information not available

CMR8734I Service error | Unable to delete data set; Reason code = {??????}

CMR8750A Service error | Address space creation failed

CMR8752I Record not found {??????} record not found

CMR8756A Function restricted | Release LINKs restricted. Contact Local Admin

CMR8758A Already Linked | LINK error - release {*release*} is already LINKed

CMR8758A Already Linked | LINK error - release {*release*} is already LINKed

CMR8760A Not Linked | UNLINK error - release {??????} is not LINKed

CMR8764A Not Linked | Release {??????} is not Linked

CMR8766A Linked Package | Release {??????} is Linked, process restricted

CMR8785A Too much storage | Query results exhausted storage, query is too general

Explanation: A release component query or search returned results that exceeded available storage.

Solution: Make the release component query or search more specific. Reduce the number of wild carded arguments or reduce the range of wild cards.

CMR8800I Invalid DSN Pattern | {??????} is an invalid DSN pattern for release datasets

Release Management Query Messages

CMR9000A Application Error | Release Id {??????} application record not found in package master

CMR9001A Invalid Date | {*date*} is an invalid Gregorian date for query component function

CMR9002A Invalid Date Range | FROM date {*date*} is more current than the TO date for query component function

CMR9003I No Components Found | No release components were found in this query

Release Area Promotion Messages

CMR3292I Promotion Error | {??????} is currently promoted to this level {??????}

CMR9500I Undefined Promotion | {??????} Promotion {??????} for {??????} is undefined

CMR9501I Promotion Updated | Area Promotion {??????} has been successfully updated

CMR9502A Promotion Deleted | Area Promotion {??????} has been successfully deleted

CMR9503A Undefined Promotion | Application {*application*} has no promotion sites defined

CMR9504A Undefined Promotion | Application {*application*} promotion site {*site*} has no promotion levels defined

CMR9505A Promotion Defined | All promotion possible already defined for Area {*area*}

CMR9506I Authorization Failed | Not allowed to promote/demote from site {*site*} level {??????}

CMR9507I No Packages Selected | No packages were selected for processing

CMR9508I No Packages Found | No release packages for {??????} for application {*application*}

CMR9509I No Libraries Found | Application {*application*} has no promotion libraries for {??????}

CMR9510I No Promotion History | No promotion history found for site {*site*} level {??????}

CMR9511I Invalid Date | {*date*} is an invalid Gregorian date for {??????} function

CMR9512I Invalid Date Range | FROM date {*date1*} is more current than the TO date {*date2*}

CMR9513I No Promotion History | No component history found for site {*site*} level {??????}

CMR9514I No Overlays Found | No Component overlays found for site {*site*} level {??????}

CMR9515I No Components Selected | No Components were selected for processings

CMR9516I Promotion Submitted | Area {*area*} promotion jobs submitted for {??????}

CMR9517I Demotion Submitted | Area {*area*} demotion jobs submitted for {??????}

CMR9518I Demotion Submitted | Package {*package*} demotion jobs submitted for {??????}

CMR9519I Components Disallowed | Components selected can not be processed for this request

CMR9520I Package Promoted | {??????} demotion {??????} release {??????} required

CMR9521I Package Not Promoted | Package {*package*} is not promoted to any release sites

CMR9522I Demotion Required | Demotion from {??????} required before promotion allowed

CMR9523I Demotion Required | Demotion from {??????} required for unblock of area {*area*}

CMR9523I Demotion Required | Demotion from {??????} required for unblock of area {area}

CMR9524I Demotion Required | Demotion from {??????} required for {??????}

CMR9525A Promotion Defined | All possible promotion already defined for Application {application}

CMR9530I Promotion Denied | Promotion to {??????} must be done from ERO

CMR9531I Promotion Denied | Promotion to {??????} must be done from ERO{??????}

CMR9540I Promotion Error | All possible components already promoted to{??????}

CMR9541I Undefined Promotion | Application Area Promotion for {??????} is undefined

CMR9550I Storage Error | Memory unavailable for the {??????} Getmain RC {returncode}

CMR9560I Promotion Error | Full Promotion not allowed to lower levels, use selective

CMR9565I Demotion Error | All Packages not at level {??????} or 00, use selective demotion

CMR9566I Demotion Error | Package not at selected level, use selective demotion

CMR9567I Demotion Error | There is nothing to demotion, Package(s) are at level 00

CMR9568I Not Qualified | No components selected for Promote qualify for area {area}

3. Legal Notice

For information about legal notices, trademarks, disclaimers, warranties, export and other use restrictions, U.S. Government rights, patent policy, and FIPS compliance, see <https://www.microfocus.com/about/legal/>.

© Copyright 2023 Micro Focus or one of its affiliates.

The only warranties for products and services of Micro Focus and its affiliates and licensors ("Micro Focus") are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. Micro Focus shall not be liable for technical or editorial errors or omissions contained herein. The information contained herein is subject to change without notice.

Third-Party Notices

Additional third-party notices, including copyrights and software license texts, can be found in a 'thirdpartynotices' file in the root directory of the software.

Specific notices

In accordance with the GNU General Public License version 2 with Classpath Exception, you are entitled to the complete OpenJDK source code that went into the JRE used by this product which includes the source code for 3 subclasses of that standard OpenJDK; MultipleGradientPaint, MultipleGradientPaintContext and TypeResolver. Please contact product support if you wish to obtain the source code. This source code will be available for 3 years from the general availability date for version 17.0 SP1.